



Battery: LR-61

PRODUCT DESCRIPTION

Compact pocket size 3½ digit multimeters. They are ideal for use by electricians, electronic engineers, general industry and laboratories. A single positive click action rotary selection switch provides ease of use. They offer multi-function measurement capability and 220Vrms overload protection. Note: 10A range is unfused.

- Impact-resistant ABS plastic case
- 22mm LCD display with large digits and function indicators
- Manual ranging via single positive click action rotary switch
- Auto polarity indication
- Fast blow fuse for overload protection
- Supplied with 2 test leads and battery

TECHNICAL SPECIFICATIONS

	Voltage AC	Voltage DC
Range	200V, 750V	200mV, 2000mV, 20V, 200V, 1000V
Resolution	100mV, 1V	100µV, 1mV, 10mV, 100mV, 1V
Accuracy	±1.2% ±10 digits	±0.5%DCV ±2 digits
Current DC		
Range	200µA (MDM-830D only) 2000µA, 20mA, 200mA, 10A	
Resolution	100nA, 1µA, 10µA, 100µA, 10mA	
Accuracy	±1.2% ±2 digits	
Resistance (Ohms)		
Range	200Ω, 2000Ω, 20KΩ, 200KΩ, 2000KΩ	
Resolution	100mΩ, 1Ω, 10Ω, 100Ω, 1KΩ	
Accuracy	±0.8% ± 2 digits	
Diode Test	Max open circuit 2.8V	
Continuity	Audible beeper if resistance is less than 100Ω	